

## BS 18 LTX Quick (602193840) Cordless drill / screwdriver 18V; metaBOX 145 L

Order no. 602193840  
EAN 4007430287007



Product may differ from image



- Robust drill/screwdriver with maximum power for demanding applications
- Metabo quick system: quick exchange of chucks, bit holders, angle adapters and more for flexible work
- Selectable "impuls" mode for removal of stubborn screws and for spot-drilling on smooth surfaces
- Robust, durable gear housing made from aluminium die-cast
- Spindle with magnetic hexagon recess for screwdriver bits for working without chuck
- Powerful Metabo 4-pole motor for fast drilling and screwdriving
- Overload protection: protects the motor from overheating
- Euro collar (Ø 43 mm) for versatile use
- Integrated working light to illuminate the contact area
- Handy belt hook, can be fixed either on the right or left side
- With metaBOX, the intelligent solution for transport and storage
- Many brands, one battery pack system: This product can be combined with all 18V battery packs and chargers of the CAS brands: [www.cordless-alliance-systems.com](http://www.cordless-alliance-systems.com)

## Technical data

### Characteristics

Battery voltage	18 V
Maximum torque, soft	55 Nm / 487 in-lbs
Pulse torque	60 Nm / 531 in-lbs
Maximum torque, hard	110 Nm / 974 in-lbs
Adjustable torque	1.5 - 24 Nm // 13 - 212 in-lbs
Drill Ø steel	13 mm / 1/2 "
Drill-Ø soft wood	65 mm / 2 1/2 "
No-load speeds	0 - 500 / 0 - 1700 rpm
Chuck capacity	1.5 - 13 mm // 1/16 - 1/2 "
Collar diameter	43 mm / 1 11/16 "
Weight without battery pack	1.7 kg / 3.7 lbs
Weight with battery pack	2.1 kg / 4.6 lbs

### Vibration

Drilling in metal	2.5 m/s <sup>2</sup>
Uncertainty of measurement K	1.5 m/s <sup>2</sup>
Screwdriving without impact	2.5 m/s <sup>2</sup>
Uncertainty of measurement K	1.5 m/s <sup>2</sup>

### Noise emission

Sound pressure level	80 dB(A)
Sound power level (LwA)	91 dB(A)
Uncertainty of measurement K	3 dB(A)

## Scope of delivery

Quick-change chuck  
 Belt hook  
 metaBOX 145 L  
 without battery pack, without charger  
 Quick-change bit holder  
 Side handle