

WVB 18 LTX BL 15-125 Quick (601731840) Cordless angle grinder 18V; metaBOX 165 L; with brake, speed control, quick-locking nut

Order no. 601731840

EAN 4061792230316



Product may differ from Image



- Brushless cordless angle grinder of the new generation: the most powerful one in its class, as powerful as a 1,500 Watt mains-powered tool
- Service-free Brushless motor with highest efficiency and maximum handiness
- Variable speed setting with thumbwheel for working on materials requiring customised speeds, and at speeds which remain constant under load
- Fast brake system for highest user safety: Disc stops within 1.5 seconds after switching off
- M-Quick System for tool-free disc change at the touch of a button
- Tool-free adjustable guard; twist-proof
- Battery pack can be rotated in 90° steps for best ergonomics in any working position
- Metabo S-automatic mechanical safety clutch: minimises kick-back to the lowest level when the disc jams unexpectedly - for maximum user safety
- Electronic overload protection, soft start and restart protection
- Detachable dust protection filter protects motor from coarse particles
- With metaBOX, the intelligent solution for transport and storage
- Many brands, one battery pack system: This product can be combined with all 18V battery packs and chargers of the CAS brands: www.cordless-alliance-systems.com

Technical data

Characteristics

Battery voltage	18 V
Disc-Ø	125 mm
Max. cutting depth	33 mm
No-load speed	2500 - 10000 rpm
Spindle thread	M 14
Handle circumference	159 mm
Weight without battery pack	2 kg
Weight with battery pack	2.7 kg

Vibration

Surface grinding	7.1 m/s ²
Uncertainty of measurement K	1.5 m/s ²
Grinding with sandpaper	1.5 m/s ²
Uncertainty of measurement K	1.5 m/s ²

Noise emission

Sound pressure level	85 dB(A)
Sound power level (LwA)	96 dB(A)
Uncertainty of measurement K	3 dB(A)

Scope of delivery

Guard
 Inner support flange
 M-Quick flange nut
 Metabo VibraTech (MVT) side handle
 Dust Protection Filter
 metaBOX 165 L
 without battery pack, without charger