

## BS 18 LTX-3 BL Q I (603184840) Cordless Drill / Driver 18V; metaBOX 145 L

Order no. 603184840  
EAN 4061792225220



Representative picture



- Brushless 3-speed cordless drill with maximum power, ideal for demanding applications
- 3 speeds with high speed (max. 4,000/min) for expanded range of use and even faster drilling progress, especially in metal
- Metabo QuickPlus System: quickly exchange chucks, bit holders, angle adapters and more for flexible work under maximum load
- Selectable "impulse" mode for removal of damaged screws and for spot-drilling on smooth surfaces
- Precision Stop: Electronic torque control with increased precision for accurate and intricate working
- Overload protection: protects the motor from overheating
- Euro collar (43 mm diameter) for diverse applications
- Electronic safety shutdown of the motor: no kickback if the drill stops unexpectedly- for good user safety
- Integrated LED work light with afterglow function for optimal brightness in the working area
- With handy belt hook and bit case, can be fixed either on the right or left side
- With metaBOX, the smart solution for transportation and storage
- Multiple brands, one battery pack system: This product can be used with all 18 V battery packs and chargers from CAS brands: [www.cordless-alliance-system.com](http://www.cordless-alliance-system.com)

## Technical values

### Parameters

Battery voltage	18 V
Maximum torque, soft	575.3 in-lbs
Maximum torque, hard	1150.6 in-lbs
Adjustable torque	8.9 - 159.3 in-lbs
Max. capacity in steel	5/8 "
Max. capacity in soft wood	2.68 "
No-load speeds	0 - 450 / 0 - 2000 / 0 - 4000 RPM
Chuck capacity	1/16 - 1/2 "
Collar diameter	1.69 "
Weight without battery pack	4 lbs
Weight including battery pack	6.2 lbs

### Vibration

Drilling in metal	2.5 m/s <sup>2</sup>
Uncertainty of measurement K	1.5 m/s <sup>2</sup>

### Noise emission

Sound pressure level	75 dB(A)
Sound power level (LwA)	85 dB(A)
Uncertainty of measurement K	3 dB(A)

## Scope of delivery

Futuro Plus "QuickPlus" quick-change chuck  
 Side Handle  
 metaBOX 145 L  
 without battery pack, without charger