

SB 18 LTX-3 BL Q I (603185840) Cordless Hammer Drill 18V; metaBOX 145 L

Order no. 603185840
EAN 4061792225251



Representative picture



- Brushless 3-speed hammer drill with maximum power, ideal for demanding metalworking applications
- 3 speeds with high speed (max. 4,000/min) for expanded range of use and even faster drilling progress, especially in metal
- Impact drill function for drilling in masonry
- Metabo QuickPlus System: Quick change of bit retainer and bits, for flexible work at maximum load
- Selectable "impulse" mode for removal of damaged screws and for spot-drilling on smooth surfaces
- Precision Stop: Electronic torque coupling with increased precision for precise, delicate working
- Overload protection: protects the motor from overheating
- Electronic safety shutdown of the motor: no kickback if the drill stops unexpectedly- for good user safety
- With handy belt hook and bit case, can be fixed either on the right or left side
- With metaBOX, the smart solution for transportation and storage
- Multiple brands, one battery pack system: This product can be used with all 18 V battery packs and chargers from CAS brands: www.cordless-alliance-system.com

Technical values

Parameters

Battery voltage	18 V
Maximum torque, soft	575.3 in-lbs
Maximum torque, hard	1150.6 in-lbs
Adjustable torque	8.9 - 159.3 in-lbs
Max. capacity in masonry	5/8 "
Max. capacity in steel	5/8 "
Max. capacity in soft wood	2.68 "
No-load speed	0 - 450 / 0 - 2000 / 0 - 4000 RPM
Maximum impact rate	38000 BPM
Chuck capacity	1/16 - 1/2 "
Collar diameter	1.69 "
Weight without battery pack	4.4 lbs
Weight including battery pack	6.6 lbs

Vibration

Drilling in metal	3 m/s ²
Uncertainty of measurement K	1.5 m/s ²
Impact drilling concrete	25 m/s ²
Uncertainty of measurement K	1.5 m/s ²

Noise emission

Sound pressure level	98 dB(A)
Sound power level (LwA)	109 dB(A)
Uncertainty of measurement K	3 dB(A)

Scope of delivery

Futuro Plus "QuickPlus" quick-change chuck
Side Handle
metaBOX 145 L
without battery pack, without charger